



GENERATORS

www.vipergen.co.za

Kwa-Zulu Natal
 134 Shepstone Road
 New Germany, 3610
 Tel: 031-705 4104
 Fax: 031-705 4542

Gauteng
 75 Watt Street
 Meadowdale, 1614
 Tel: 011-974 0400
 Fax: 011-974 0554

Model: 30kVA 1 PHASE

POWER DATA

Voltage	Prime Power		Standby Power		Standby AC Amps Per Phase	No. of Phase
	kva	kw	kva	kw		
220V	30.0	24.0	34.0	27.2	100.0	1

ENGINE DATA

Manufacturer	R Series British Ricardo	Compression Ratio	17.0:1
Origin	British	Oil Capacity (L)	11
Model	K4100DS	Electrical System	12V
Governor Type	Mechanical	Coolant Capacity (L)	20
Speed	1500rpm	Fuel Consump. (100%load)(L/HR)	7
Prime Power (kw)	30.1	Fuel Tank Capacity (L)	154
Standby Power (kw)	30.1	Cooling	Water Cooled
Cylinder No. & Config.	4 in Line	Aspiration	Natural
Bore x Stroke (mm)	100 x 125	Displacement (L)	3.93

ALTERNATOR DATA

Manufacturer	Stamford	Voltage (V)	220
Origin	U.S	Voltage Accuracy	± 1%
Model	WHI-224C	Frequency	50Hz
Capacity (kva)	40.0kva	Insulation Class	H
Power Factor	0.8	Protection Rate	IP22
Efficiency	88%	Excitation System	Brushless, AVR
Bearing Number	Single	Connection Type	Star
Leads Number	12		

OVERALL DIMENSIONS & WEIGHT

Genset Size (mm) (L x W x H)	2210 x 900 x 1230
Net Weight (kg)	1000



KEY FEATURES

1. Durable British Ricardo Engine
2. Single Bearing Stamford Type Alternator
3. ATS & AMF
4. Four Protection Device Equipped
5. Anti-Vibration Mountings
6. Main Line Circuit Breaker
7. Factory Test Certificate
8. Noise level @7m (db): 80

STANDARD CONTROL SYSTEM

The Standard control system is based on the advanced smartgen HGM7220 Electronic Digital Controller.

This Provides for the manual and automatic remot start of generator with a LCD digital display of:

1. Coolant Temperature
2. Oil Pressure
3. Volts, Amps, Power Factor & Frequency
4. Engine Operation Hours
5. Over Current Protection
6. Under, Over Volt Protection
7. Over Temperature Protection
8. Over Speed, Low Oil Pressure Protection

