



GENERATORS

KWA-ZULU NATAL:
134 Shepstone Road
New Germany, 3610

Tel: (031) 705-4104
Fax: (031) 705-4542

GAUTENG:
75 Watt Street
Meadowdale, 1614
Tel: (011) 974-0400
Fax: (011) 974-0554



Model	12.5kVA PETROL SILENT GENERATOR
Rated Frequency (Hz)	50
Rated Voltage (V)	220
Rated Current (A)	46
Rated AC output (Kw)	10
Max AC output (Kw)	11
DC output	12V / 8.3A
Power Factor	1
Phase number	Single phase
Engine Model	HONDA GX690
Engine Type	4 stroke, 2 cylinder 90 deg. V
Engine RPM	3000
Engine Displacement	688cc
Engine Oil Capacity	1.5L
Oil Type	SAE10W-30SF
Fuel Tank Capacity	30L
Fuel Consumption	3.6L per hour
Noise level dB(A)/7m	60-65
Starting system	Hand (Electric) starter with ATS
Dimensions (mm)	1220x650x920 (L x B x H)
Weight (kg)	293